

AC40A Battery Charger

DX Series Wireless Solutions

Linking
People
Together



AC40A Battery Charger

Key Features and Benefits

- 4-port quick charger
- Charges 4 batteries simultaneously
- 6 additional battery storage slots
- LED status indicator lights
- Green LED status indicator on top and bottom
- Charge time is 2.5 hours
- Comes with an adapter, 115/230V AC
- Charges BAT41 batteries

Order Codes

AC40A

The AC40A Battery Charger is a 4-port charger for BAT41 batteries.

Description

The AC40A charger has four charging slots with LED indicator lights that displays the charging status of the each of the four batteries. Six slots are available for batteries which have already been charged or need to be charged. Diagnostic instructions are also noted on the side of the AC40A chassis. The AC40A charger comes with a 115/230V AC power supply adapter.

The AC40A charges batteries used in the BP200, BP210, BP300 and BP340 beltpacks, and the WH200, WH210, WH300 and WH340 all-in-one headsets. Once charged, the BAT41 provides up to 20 hours of beltpack or headset operation.

Technical Specifications

Dimensions
7.6 x 2.7 x 4.6in (WxHxD)
(19.4 x 6.8 x 11.8cm)

Weight
1.1oz (31.2g)



www.clearcom.com/dxseries-knowledge-center/